



# Shenzhen Blueberl Electronic Technology Co., Ltd.

3F, Building U3, U8 Intelligent Manufacturing Park, Hangcheng Avenue, Shenzhen, China 518126

Tel: +86-755-36561799 E-mail: [info@blueberl.com](mailto:info@blueberl.com)

## Specifications

◇ Main features and selling points		◇ ID appearance		
<ul style="list-style-type: none"> <li>*1.85 large screen</li> <li>*900mAh large battery</li> <li>*Video call</li> <li>*Intelligent Android system</li> <li>*LBS+GPS+WIFI multiple precise positioning</li> <li>*Fashionable appearance</li> <li>*Social media apps: WeChat Tiktok</li> </ul>				
<b>Operating system</b>		<b>Android 8.1</b>		
<b>Software function list</b>				
<b>Chip</b>	* System data type	32 place	*SMS	Receiving SMS
	* Main chip model	ASR3603S	* Dials	Free dial
	* Main frequency	1.4GHz	* mail list	Save the address book through app and display it on the watch
	* framework	Quad-core ARM® Cortex™ A53 MP processor	* Micro chat	Can send short voice messages with parents, display square
	* Number of kernels	Dual core	* Video call	After binding the watch, you can make a video call with your
<b>Radio frequency</b>	* GSM/WCDMA/FDD/TDD	GSM: B3 B8	* photograph	High definition photography
		WCDMA: B1 B8		
		TDD: B38 B39 B40 B41		
<b>Frequency band</b>	* Data rate	FDD: B1 B3 B5 B8	* Early education	Course schedule, crazy quick learning
		2G rate: GPRS	* album	Display the saved photos of the watch
		3G rate: WCDMA	* set up	Watch function settings (power off can be set by internal power off)
		4G rate: CAT4	* QR Code	Display watch registration code and app download QR code
<b>Calling Mode</b>	* VOLTE	support	* alarm clock	Three alarm clocks can be set through app
	* Video call	support	* Calculator	Tinger Calc
	* GSM call	support	* Call logs	Display the call history of the watch
<b>Storage</b>	* Memory	NOR	* Face	Can achieve local facial unlocking
	* capacity(RAM+ROM)	RAM 128Mb+built-inROM	* List of dials	Multiple sets of stunning analog dials
<b>LBS location</b>	* LBSbase station	support	* Profile	Can set watch profile
	* Positioning accuracy	100-1000M	* Migu Music	You can set the ringing tone for incoming calls on your watch
<b>GPS location</b>	* Step counting	Watch pedometer, default off	* WIFI internet	Connect to the network through WIFI
	Chip model	Integration chip	* Touch and	Can make 4 friends, good friends can make video calls
	GPS signal	L1,1575.42MHz C/A code	* Fire Rabbit	Audible story music
	Number of GPS	72passageway	* Weather	Display the current position of the watch Weather
	GPS chip reception	Tracking -163dbm,	* QQ	Children's Watch Version QQ
	GPS positioning	5-15m	* WeChat	Support for WeChat applications
	GPS antenna	LDS	* Tiktok	Brush Tiktok small video
	AGPS	support		
* GPS Fast positioning	Cold start 28 seconds			
<b>WIFI location</b>	* WiFi	Support, only RX only	<b>* APP Download QR Code</b> 	
	* WiFi Chip model	built-in		
	* WiFi standard	802.11b\802.11g\802.11n		
	* WiFi hotspot	Not Supported		
	* WiFiData	Not Supported		
* Fit mode	OGS frame paste			
* Display	1.85 "240 * 280			



Display	* Screen type	LCD		
	* Screen making	IPS		
	* size	1.85 inch		
	* Chip IC /interface	IC:ST7789V+IPS		
	* Resolving power	240*280	<b>* App function list</b>	
	* Visual angle	Full perspective	* telephone	Set the phone number through app and save it into the phone book of the watch
Touch screen	* Touch type	Capacitive	* Forbidden in	Three time periods can be set to disable classes
	* Production	COB	* Looking for	After looking for the device, the watch will ring
	* Panel shape	2D	*Video call	You can make video calls with parents' mobile phones or watches that have friends
	* Panel thickness	1.1mm	* Friend business card	You can use the device to make friends, two watches in the same location can make friends
	* Anti fingerprint oil	yes		
	* Touch points	Single point	* Love reward	The number of love awards can be set
Camera	* Front camera pixels	30W	Refuse to receive unfamiliar calls	You can set the number of strange calls on your watch
	* Lens type	CMOS		
	* Proactive IC	GC030A	* SOS number	Three groups of SOS numbers can be set
Battery	* Cell specification	603032	* Equipment	Through the alarm function of APP device Watch
	* Battery capacity	900mAh High voltage	* SMS reminder	Low power reminder for SOS security area of communication app
	* Cell type / voltage	Polymer battery \4.35V	* Working mode	The interval of positioning time can be set
	* Standby current	6mA	* remote	Watch shutdown can be set through app
	* Theoretical standby	100H	* Reset device	The watch factory settings can be restored through app
	* Charging current	300mAH	* Switch settings	You can set the watch dial to open and lock
	* Charging time	2.5H	* Unbinding	You can unbind the binding status of the watch and app
Structure appearance	* Appearance size	243-42-16mm	* Map	Displays the geographical location of the watch
	* Weight	63g	* footprint	Show the footprint of the watch
	* Colour	Blue,Pink, Black	* Electronic	Electronic fence for watch can be set
	* Boot key	Physical keys / SOS compatible	*App store	allows you to download apps to children's watches from within the app
	* Antenna technology	LDS antenna		
	* Whole machine	Pure PC spray UV oil		
	* Watch strap			
Peripheral	* Horn	1609 waterproof horn		
	* Microphone	Waterproof and strong anti-		
	* Charging mode	USB charging / customized		
	* Motor specification /	Support		
	* SIM card holder /	Cato nano card		
Packing Information	* Instruction card	a sheet	Packaging size	14.6*8.3*5.1cm
	* Charging line	One	Product size	243-42-16mm
	* Certificate	a sheet	Single packaging	144g
	*Screwdriver	One	Outer box size	435*310*125mm
	*Card reader	One	Weight (full box)	3.6Kg///20PCS/CTN